Cum se configureaza camerele IP SAFER WIRELESS

VARIANTA 1 (WIFI)

- 1. Descarcati aplicatia GUARD VIEWER (disponibila pe APP Store sau PLAY STORE)
- 2. Faceti un cont si pastrati USERUL si PAROLA intr-un loc sigur
- 3. Intrati pe aplicatie, dati pe + pentru a adauga o camera
- 4. Selectati ADD WI-FI DEVICE, selectati tipul de camera.
- 5. Luati manualul camerei de supraveghere, acolo aveti un cod QR.
- 6. Bifati " Camera is ready to read QR code"
- 7. Selectati ADD as local DEVICE

3		4			6/7	
orange 🗢 15:07 32% 🗊	III orange 🗢	15:07	32 % 💼	15:36 D	ic	¥ 🗟 II 26% 🛢
E Q Enter the device name	E <	Add By	Я	<	Prepare	×
(bbA+)	8	Scan		Make sure	the camera is covere network	ed by Wi-Fi
	(free	Manual Add		Start the ca light or gree the ca	mera and wait for about 3 en light flashes slowly (1/s imera is ready to read QR	0s till the IR s). It means code.
	Q	Auto Search in LAN				
	Ŷ	Add Wi-Fi Device			061	
No device has been added yet.						
				S c	amera is ready to read QR Abnormal status?	code
					Add As Cloud Device	0
					Add As Local Device	0
				III	0	<

- 8. Denumiti camera, selectati routerul DVS, introduceti parola routerului (este posibil sa fie vazuta automat), apasati pe scanner-ul QR pentru a scana codul de inregistrare (REGISTER CODE)
- 9. Scanati codul QR de pe manual.

<	Configure Device	×
Please ke	ep the mobile phone close to the device 5G Wi-Fi is not supported	•
Enter the devic	e name papa	
Wi-Fi	ZyX	>
Wi-Fi Password	d	
Register Code	5ECVUBQAGEJ01YH05D4D7d	
Where is the re	egister code?	
	Next	

10. Apoi se va afisa un cod QR pe telefon, acesta trebuie scanat cu camera (*sa o tineti la maxim 10-15 cm de codul QR afisat pe telefon).



11. Dupa 10 secunde, dispozitivele vor fi imperecheate si veti primi un mesaj de succes.

Acum o vom adauga pe contul de CLOUD, astfel o veti putea accesa dintr-o retea externa.

12. Intrati pe STAR4LIVE.COM , folositi acelasi cont ca cel din aplicatia GUARD VIEWER (de la punctul 1)

Sta	Live	in Signu	p Help
	Log In		
	Usemame/Email:		
	Password:		
	Login Forgot password?		

13. Apasati pe ADD DEVICE

Star 4Li v	ve								We	elcome sori 🗸	Exit Help
📃 Device List	📃 Org List								+ Ad	ld Org 🕇 🕂 A	Add Device
oot	My Cloud D	evices									â
	Select No.	Org	Device Name	Device Type	Device IP	Latest Onlin Time	ne Status	Share Device	Change Device	Retrieve Password	Access Device
					No devi	ce. Click Add E	Device to add				
	Shared Clou	Id Device	95								Ê
	Select No.	Org	Device N	lame	Device IP	Owner	Valid Until	Description	Status	Change Devic	e Access Device
					No devi	ce. Click Add E	Device to add				
	Sharing Rec	ords	a de la companya de la								â
	Select	No.	Device Name	Shar	re To E	Email	User Role	Vali	d Until	Desc	ription

14. Introduceti codul dispozitivului (il gasiti pe manualul de utilizare sau in aplicatia GUARD VIEWER). Alegeti orice nume doriti pentru dispozitiv. Apasati pe butonul albastru "ADD"

Star4Liv	'e				Welcome s	ori 🗸 Exit Help
\Xi Device List	📃 Org List				+ Add Org	+ Add Device
Add Device						
		Register Code:				
		Device Name:				
		Org Name:	root	Select		
			Add Back			

15. Acum puteti sa o accesati si pe telefon, automat in aplicatia GUARD VIEWER

Cum se configureaza camerele IP SAFER WIRELESS

VARIANTA 2 (LAN)

- 1. Folositi un patchcord pentru a conecta camera la retea.
- 2. Descarcati aplicatia GUARD VIEWER (disponibila pe APP Store sau PLAY STORE)
- 3. Faceti un cont si pastrati USERUL si PAROLA intr-un loc sigur
- 4. Intrati pe aplicatie, dati pe + pentru a adauga o camera
- 5. Selectati AUTO SEARCH IN LAN
- 6. Veti vedea mai multe dispozitive, sau doar unul. Denumirea camerei se termina cu (IPC)

	4		5				6	
📶 orange 🗢	15:07	32 % 💶	📶 orange 🗢	15:07	32 % 💼	📶 orange 🗢	15:09	32 % 💶
\equiv	Live View	⊊ı.	<	Add By	R	<	Auto Search in LAN	
						Select All		0
				Scan		192.10	68.1.214()	0
			łm	Manual Add		192.10	88.1.215()	0
	(\pm)					192.10	68.1.229(IPC)	0
			Q	Auto Search in LAN				
			(;	Add Wi-Fi Device				
[O]		Low 🗐×						
	1/1							
	Playback	>						
Alarm Out	<	Favorites Close All					Add(0)	

- 7. Deschideti un browser pe un PC/Laptop si introduceti IP-ul camerei
- 8. Aici se va deschide o fereastra de log-in (userul si parola implicita este admin/123456, va recomandam sa le schimbati dupa setarea camerei)

Safer	SAF-IPCBP2MP30-4(W)
Username Password	
	Live View Login Reset

9. Intrati la NETWORK \rightarrow NETWORK \rightarrow WI-FI

Safer .	ve View 🔅 Setup			SAF-IPCBP2MP30-4(W) ●Logo
Common	Basic Info			
Network	Basic Info		Common Configuration	
Network	Model	SAF-IPCBP2MP30-4(W)		
DNS	Firmware Version	IPC_D1202-B0006P20D1812C09	Ethernet	
Port	Hardware Version	A		
DDNS	Boot Version	V1.1	Time	
P2P	Serial No.	210235TCX33198000046		
E-mail	Network	192.168.	OSD OSD	
003	MAC Address	e4:f1		
Video				
Image	Status		User User	
Intelligent	System Time	2011/11/30 16:11:49		
Events	Operation Time	0 Day(s) 0 Hour(s) 11 Minute(s)		
Storage	Refresh			
Security				

Common	Ethernet	Wi-Fi		
Network	Obtain IP A	drace	DHCP	T
Network		Juless	Dife	
DNS	IPv6 Mode		Manual	•

10. Schimbati din WI-FI Hotspot in WI-FI, mai jos va aparea o lista cu retelele din apopiere. Selectati reteaua dumneavoastra si introduceti parola.

ommon	Ethernet Wi-Fi	
etwork		100 E U.L.
 Network 	WI-FI Mode	VVI-FI Hotspot
Network	COID	IDCW/E/1691CE
DNS	SSID	IPCWIF11661C5
Port	Password	••••••
DDNS	Channel	Automatic •
P2P	Gateway Address	172.16.0.1
E-mail		

Common	Ethernet Wi-Fi					
Network			_			
b. Mahundi	Wi-Fi Mode	Wi-Fi	•			
DNIC	Adaptive Streams	0 On @ Off				
Divis	Current Status	Disconnected				
DDNS	SSID	None				
DDD	IP Address	0.0.0.0				
P2P	Subnet Mask	0.0.0.0				
E-mail	Default Gateway	0.0.0.0				
Qos	Strength	ail				
lideo						
mage	Wi-Fi Network					
ntelligent	Search					
vents	SSID	Channel MAC Address	Authentication	Encryption	Strength	Strength(dBm)
torage	1. Retea wireless		WPA-PSK WPA2-PSK	CCMP	atl	-46
	2. Retea imprima	nta	WPA-PSK WPA2-PSK	CCMP	atl	-62
scurity	3. Retea wireless	extender	WPA-PSK WPA2-PSK	CCMP	atl	-63
ystem	4. Retea wireless	2	WPA-PSK WPA2-PSK	CCMP	attl	-76
	5. Retea wireless	3	WPA-PSK WPA2-PSK	CCMP	attl	-79
	6. Retea firma		WPA-PSK WPA2-PSK	CCMP	atl	-82
	7. Zapp		WPA-PSK WPA2-PSK	CCMP	attl	-86
	NAVI EL					
	COLD		- <i>/</i>			
	Barrword					
	Encryption	None				
	Authentication	OPEN	·			
	Authentication		-			

11. Camera este configurata pentru a functiona pe wireless. Puteti sa deconectati cablul (PatchCord)

Acum o vom adauga pe contul de CLOUD, astfel o veti putea accesa dintr-o retea externa.

12. Intrati pe STAR4LIVE.COM , folositi acelasi cont ca cel din aplicatia GUARD VIEWER (de la punctul 3)

Log In	
Username/Email:	
Password:	
Login Forgot password?	

13. Apasati pe ADD DEVICE

	C										
📃 Device List	🗮 Org List							+ Ad	ld Org 🕂	Add Device	
🖸 root	My Cloud Devic	My Cloud Devices									
	Select No. C	org Device Name	Device Type	Device IP	Latest Online Time	Status	Share Device	Change Device	Retrieve Password	Access Device	
		No device. Click Add Device to add									
	Shared Cloud E	Devices									
	Shared Cloud D Select No.	Devices Org Device	Name	Device IP	Owner V	/alid Until	Description	Status	Change Devie	Ce Access Device	
	Shared Cloud E Select No.	Oevices Org Device	Name	Device IP No devi	Owner V	/alid Until ce to add	Description	Status	Change Devi	Ce Access Device	
	Shared Cloud D Select No.	Org Device	Name	Device IP No devi	Owner V ice. Click Add Devie	Valid Until ce to add	Description	Status	Change Devie	Access Device	
	Shared Cloud D Select No.	Org Device State	Name	Device IP No devi	Owner V	/alid Until ce to add	Description	Status	Change Devic	Access Device	
	Shared Cloud I Select No.	Org Device Is Device Name	Name sha	Device IP No devi	Owner V ice. Click Add Devis Email Use	Valid Until ce to add er Role	Description	Status d Until	Change Devic	Ce Access Device	

14. Introduceti codul dispozitivului (il gasiti fie pe manualul de utilizare, fie in interfata camerei, pe care o puteti accesa ca la pasul 8, in meniul NETWORK→P2P). Alegeti orice nume doriti pentru dispozitiv. Apasati pe butonul albastru "ADD"

Star4Live		Welcom	e sori 🗸 Exit Help
🗮 Device List 🗮 Org List		🕂 Add Or;	+ Add Device
① Add Device			
	Register Code:		
	Device Name:		
	Org Name: root	Select	
	Ado Back		

15. Acum puteti sa o accesati si pe telefon, automat in aplicatia GUARD VIEWER