


SICHERHEITSANLEITUNGEN

- Lesen Sie aufmerksam die Bedienungsanleitung bevor Sie das Gerat benutzen... 1. Schutzen Sie dieses Produkt vor Feuchtigkeit, Nasse, Wasser und anderen Flussigkeiten...

PRODUKTDESCHEIBUNG

- 1. Taste WPS/ Zurücksetzen: Drucken (etwa 1 Sekunde) um die WPS Funktion zu aktivieren... 2. Netzaste: drucken und halten um das Gerat ein-/ auszuschalten...



BEDIENUNG

Der Repeater hat 2 Funktionen: er kann als Repeater und als Zugangspunkt (Access point) funktionieren.

EINSTELLEN DES WI-FI REPEATER

Es gibt zwei Moglichkeiten um das Gerat als Wi-Fi Repeater einzustellen, mit WPS oder mit Internetkabel (ohne WPS Funktion).

Einstellen mit WPS

- Wenn Sie mit der WPS-Taste einstellen mochten, stellen Sie bitte sicher, dass der Router (mit dem Sie eine Verbindung herstellen mochten) auch eine WPS-Funktion hat... 1. Verbinden Sie den Wi-Fi Repeater mit Ihrem vorhandenen Router durch die WPS Taste...

Die Standard Wi-Fi SSID fur den Repeater nach dem Einstellen mit WPS-Funktion: Mlife (ohne Passwort).

Einstellen mit Internetkabel (ohne WPS)

- 2. Verbinden Sie den Wi-Fi Repeater mit Ihrem vorhandenen Router ohne WPS: 1. Stecken Sie den Wi-Fi Repeater in eine Steckdose in der Nahe Ihres vorhandenen Routers... 2. Geben Sie 192.168.10.1 in der Adressleiste in Ihrem Webbrowser ein...



- f. Alle verfugbaren Wi-Fi Netzwerke werden in einem Bildschirm angezeigt... g. Wahlen Sie das gewunschte Netzwerk aus und geben das Passwort fur dieses Netzwerk ein...

Anmerkung: Die Standard Wi-Fi SSID fur den Repeater nach dem Einstellen mit Internetkabel ist die vorhandene Wi-Fi Router SSID + -ext. Zum Beispiel, wenn der vorhandene Wi-Fi Router die SSID "ABC" hat, hat der Repeater die SSID "ABC-ext" nach dem Einstellen.

VERBINDEN VON EXTERNEN GERATEN AM REPEATER

- 1. AnschlieBen Ihres Laptops, Mobiltelefon, oder Tablet am Wi-Fi Repeater... a. Sie konnen nun den Wi-Fi Repeater in die ausgewahlte Steckdose stecken... b. Suchen Sie nach neuen Wi-Fi Verbindungen an Ihrem Mobilgerat...

LED ANZEIGE:

- flackert schnell - vor der Verbindung mit dem Router... flackert langsam - nach Drucken der WPS Taste wahrend die Verbindung mit dem Router mit WPS-Funktion hergestellt wird... leuchtet konstant - nach der Verbindung mit dem Router

VOREINGESTELLTE DATEN

Benutzername (username): admin
Passwort (passwort): admin
IP Adresse: 192.168.10.1
SSID: Mlife (Achtung: ohne Passwort)


FEHLERBEHEBUNG

Auf Werkseinstellungen zurucksetzen
Bei eingeschaltetem Gerat, drucken Sie die Taste Zurucksetzen auf der Hinterseite des Gerates fur 5 bis 10 Sekunden, wiederherstellen der Werkseinstellungen.

Warum kann ich die Anmeldeseite nicht sehen, nachdem ich http://192.168.10.1 im Browser eingegeben habe?

- Vergewissern Sie sich, dass Ihr PC oder Telefon mit dem Erweiterungs-Netzwerk verbunden ist und von allen anderen Netzwerken getrennt ist... Vergewissern Sie sich, dass Ihr PC oder Telefon so eingestellt ist, dass er automatisch eine IP-Adresse erhalt.

Mein Erweiterungssignal ist schwach und verschwindet oft. Bitte stellen Sie den Repeater optimal auf.



(Anzuwenden in den Landern der Europaischen Union und anderen europaischen Landern mit einem separaten Sammelsystem) Die Kennzeichnung auf dem Produkt bzw. auf der dazugehorigen Literatur gibt an, dass es nach seiner Lebensdauer nicht zusammen mit dem normalen Haushaltsmull entsorgt werden darf.

SAFETY INSTRUCTIONS

Read the instruction manual carefully before first use and keep it for future reference.

- 1. Protect this product from moisture, humidity, water and any other liquid... 2. Keep the device beyond children's reach... 3. Product suitable for indoor use only... 4. Disconnect the device from the power supply if it is not going to be used for a long time...

PRODUCT DESCRIPTION

- 1. WPS/reset button: press to activate WPS function (around 1 sec.)... 2. Power button: press and hold to switch the device on/off... 3. RJ45 socket

OPERATION

The repeater has 2 functions: it can work as a Repeater and as an Access point.

CONFIGURATION OF THE WI-FI REPEATER

There are two ways to set up this device as Wi-Fi repeater, with WPS or with internet cable (without WPS function).

Setting with WPS

- If you want to setup with WPS button, please make sure that the router (that you want to connect with) also has a WPS function... 1. Connect the Wi-Fi repeater to your existing router by WPS button... 2. Press WPS button on your existing router... 3. Press and hold WPS button on the repeater for about 1 second to activate the WPS function on the repeater...

Remark: The default Wi-Fi SSID for the repeater after setup with the use of WPS function is "Mlife" (no password).

Setting with internet cable (without WPS)

- 2. Connect the Wi-Fi repeater to your existing router without WPS: a. Plug the Wi-Fi repeater into a power outlet near your existing router... b. Connect one plug of the internet cable into the Wi-Fi repeater (RJ45 LAN port) and plug the other end in your external device... c. Enter 192.168.10.1 in address bar in your web browser... d. Enter admin in both the username and password field...



- f. All available Wi-Fi networks will be shown in a screen... g. Select desired network and enter password to this network... h. Click Save button. Wait at least 90 seconds as the settings are being saved...

Remark: The default Wi-Fi SSID for the repeater after setup via internet cable is existing Wi-Fi router SSID + -ext. For example if existing Wi-Fi router has the SSID "ABC", the repeater will have the SSID "ABC-ext" after setup.

CONNECTING EXTERNAL DEVICE TO THE REPEATER

- 3. Connect your laptop, mobile phone or tablet to the Wi-Fi repeater... a. You can now insert the Wi-Fi repeater in the selected power outlet... b. Search for new Wi-Fi connections from your mobile device... 4. Connect an end device to the Wi-Fi repeater using WPS: a. Activate WPS on your peripheral device... b. Press the WPS button on the Wi-Fi repeater for about 1 second...

LED STATUS:

- flickering fast - before connecting to router... flickering slow - after pressing the WPS button when connecting to router via WPS... constant light - after establishing successful connection to router

DEFAULT DATA

Username: admin
Password: admin
IP address: 192.168.10.1
SSID: Mlife (Note: no password)

TROUBLESHOOTING

- How to reset to defaults? While the power is still on, keep pressing the reset button on the behind side of the product for 5 to 10 seconds... Why cannot I see the login page after entering http://192.168.10.1 in the browser? make sure your PC or phone is connected to the extender network... make sure your PC or phone is set to obtain an IP address automatically.

My signal from the range extender is weak, and keeps dropping off. Place the extender in an optimum location. Make sure the repeater is within router's range.



(Applicable in the European Union and other European countries with separate collection systems) This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life.

